

# NASA TECH BRIEF


*Ames Research Center*



NASA Tech Briefs announce new technology derived from the U.S. space program. They are issued to encourage commercial application. Tech Briefs are available on a subscription basis from the National Technical Information Service, Springfield, Virginia 22151. Requests for individual copies or questions relating to the Tech Brief program may be directed to the Technology Utilization Office, NASA, Code KT, Washington, D.C. 20546.

## Multiloop Distributed RC Active Networks

Analysis has shown that the use of a distributed RC active two-port network and a voltage amplifier provides a unique advantage over the use of lumped elements in that an essentially second-order band-



pass function can be obtained with a single distributed passive element (a monolithic distributed RC structure). This results in an active RC filter having "zero"  $Q$  sensitivity to passive element variation, which is desirable for performance stability with integrated networks. The voltage gain required even for high  $Q$  in a single-loop (positive or negative feedback) network is less than one, but the  $Q$  sensitivity to amplifier gain change is very high. The incorporation of both positive and negative feedback loops (see fig.) provides a considerable improvement in  $Q$ , sensitivity, and gain- $Q$  sensitivity product compared to the single-loop networks.

The amplitude response of the network was measured when operating with  $K_1 = 0.59$  and  $K_2 = 4.0$  ( $K_1$  and  $K_2$  being the voltage gains).

Compared to an expected  $Q$  of 50 under these conditions, the measured  $Q$  was 49. The expected frequency of a peak response using these values (and RC time constant =  $109 \mu s$ ) is 28 kHz, compared to a measured value of 26 kHz. The difference is probably due to a small amount of amplifier phase shift at the operating frequency. The improvement in stability (gain-sensitivity product) for a given  $Q$  is about a factor of 6.

Design equations have been developed to allow various optimizations depending on the specific requirements: for example, equal  $Q$  sensitivities to change in the gain of either amplifier, or equal gain-sensitivity products for the two amplifiers. The use of the distributed-RC multiloop network not only eliminates the  $Q$  sensitivity to passive-element variation, and reduces the  $Q$  sensitivity to gain change, but also allows frequency tuning by varying the dc bias on a depletion layer capacitance in the monolithic distributed-RC structure without affecting the resonant  $Q$ .

### Note:

Requests for further information may be directed to:

Technology Utilization Officer  
Ames Research Center  
Moffett Field, California 94035  
Reference: TSP71-10177

### Patent status:

No patent action is contemplated by NASA.

Source: William J. Kerwin  
Ames Research Center  
(ARC-10200)

Category 01